

PAARD

PATCH LIST GROLSCH ZAAL

16/01/2025

Desk

GrandMA3 Fullsize (Latest firmware)

sACN

ELC Node 8 IP 2.0.1.1

House Desk (MA3) IP 169.254.196.54 Priority 150

Guest Desk IP 2.0.1.3 priority 100

Universe 1 Front + side

Universe 2 LX1

Universe 3 LX2

Universe 4 LX3

Universe 5 Hall + haze

Universe 6 Free

Universe 7 Floor

Universe 8 Free

Universe 1 – Dimmers / Side stage

Nr.	Fixture Name	Location	DMX Address	Mode	Notes
1	Chauvet Ovation E-260 WW Profile	Front Bridge	1.101	6 channel	
2	Chauvet Ovation E-260 WW Profile	Front Bridge	1.107	6 channel	
3	Chauvet Ovation E-260 WW Profile	Front Bridge	1.113	6 channel	
4	Chauvet Ovation E-260 WW Profile	Front Bridge	1.119	6 channel	
5	Chauvet Ovation E-260 WW Profile	Front Bridge	1.125	6 channel	
6	Chauvet Ovation E-260 WW Profile	Front Bridge	1.131	6 channel	
7	Chauvet Ovation E-260 WW Profile	Front Bridge	1.137	6 channel	
8	Chauvet Ovation E-260 WW Profile	Front Bridge	1.143	6 channel	
9	Chauvet Ovation E-260 WW Profile	Front Bridge	1.149	6 channel	
10	Chauvet Ovation E-260 WW Profile	Front Bridge	1.155	6 channel	
11	Chauvet Ovation E-260 WW Profile	Front Bridge	1.161	6 channel	
12	Chauvet Ovation E-260 WW Profile	Front Bridge	1.167	6 channel	
1	Chauvet Rogue R1 Beamwash	Side Stage Left	1.301	15 channel	
2	Chauvet Rogue R1 Beamwash	Side Stage Left	1.316	15 channel	
3	Chauvet Rogue R1 Beamwash	Side Stage Left	1.331	15 channel	
4	Chauvet Rogue R1 Beamwash	Side Stage Right	1.346	15 channel	
5	Chauvet Rogue R1 Beamwash	Side Stage Right	1.361	15 channel	
6	Chauvet Rogue R1 Beamwash	Side Stage Right	1.376	15 channel	

Universe 2 Stage LX1

Nr.	Fixture Name	Location	DMX Address	Mode	Notes
1	Chauvet Maverick force 2 Profile	LX1	2.001	50CH	
2	Chauvet Maverick force 2 Profile	LX1	2.051	50CH	
3	Chauvet Maverick force 2 Profile	LX1	2.101	50CH	
4	Chauvet Maverick force 2 Profile	LX1	2.151	50CH	
5	Chauvet Maverick force 2 Profile	LX1	2.201	50CH	
6	Chauvet Maverick force 2 Profile	LX1	2.251	50CH	
1	Chauvet Maverick force 2 Beamwash	LX1	2.301	Basic 2 (25CH)	
2	Chauvet Maverick force 2 Beamwash	LX1	2.326	Basic 2 (25CH)	
3	Chauvet Maverick force 2 Beamwash	LX1	2.351	Basic 2 (25CH)	
4	Chauvet Maverick force 2 Beamwash	LX1	2.376	Basic 2 (25CH)	
1	Chauvet Color Strike M	LX1	2.401	68CH	Full pixel modus(JDC 1 clonable)
1	Chauvet Strike Array 2	LX1	2.473	9CH	Separate amber and white
2	Chauvet Strike Array 2	LX1	2.482	9CH	Separate amber and white
3	Chauvet Strike Array 2	LX1	2.491	9CH	Separate amber and white
4	Chauvet Strike Array 2	LX1	2.500	9CH	Separate amber and white

Universe 3 Stage LX2

Nr.	Fixture Name	Location	DMX Address	Mode	Notes
1	Chauvet Maverick force 2 Profile	LX2	3.001	50CH	
2	Chauvet Maverick force 2 Profile	LX2	3.051	50CH	
3	Chauvet Maverick force 2 Profile	LX2	3.101	50CH	
4	Chauvet Maverick force 2 Profile	LX2	3.151	50CH	
1	Chauvet Maverick force 2 Beamwash	LX2	3.201	Basic 2 (25CH)	
2	Chauvet Maverick force 2 Beamwash	LX2	3.226	Basic 2 (25CH)	
3	Chauvet Maverick force 2 Beamwash	LX2	3.251	Basic 2 (25CH)	
4	Chauvet Maverick force 2 Beamwash	LX2	3.276	Basic 2 (25CH)	
5	Chauvet Maverick force 2 Beamwash	LX2	3.301	Basic 2 (25CH)	
6	Chauvet Maverick force 2 Beamwash	LX2	3.326	Basic 2 (25CH)	
1	Chauvet Color Strike M	LX2	3.351	68ch	Full pixel modus(JDC 1 clonable)
2	Chauvet Color Strike M	LX2	3.419	68ch	Full pixel modus(JDC 1 clonable)
1	Chauvet Strike Array 2	LX2	3.491	9CH	Separate amber and white
2	Chauvet Strike Array 2	LX2	3.500	9CH	Separate amber and white

Universe 4 Stage LX3

Nr.	Fixture Name	Location	DMX Address	Mode	Notes
1	Chauvet Maverick force 2 Profile	LX3	4.001	50CH	
2	Chauvet Maverick force 2 Profile	LX3	4.051	50CH	
1	Chauvet Maverick force 2 Beamwash	LX3	4.101	Basic 2 (25CH)	
2	Chauvet Maverick force 2 Beamwash	LX3	4.126	Basic 2 (25CH)	
1	Chauvet Color Strike M	LX3	4.201	68CH	Full pixel modus(JDC 1 clonable)
2	Chauvet Color Strike M	LX3	4.269	68CH	Full pixel modus(JDC 1 clonable)
3	Chauvet Color Strike M	LX3	4.337	68CH	Full pixel modus(JDC 1 clonable)
1	Chauvet Strike Array 2	LX3	4.473	9CH	Separate amber and white
2	Chauvet Strike Array 2	LX3	4.482	9CH	Separate amber and white
3	Chauvet Strike Array 2	LX3	4.491	9CH	Separate amber and white
4	Chauvet Strike Array 2	LX3	4.500	9CH	Separate amber and white

Universe 5 – Hall

Nr.	Fixture Name	Location	DMX Address	Mode	Notes
1	Rush by Martin MH6	Hall bridge 1	5.001	14 channel	
2	Rush by Martin MH6	Hall bridge 1	5.015	14 channel	
3	Rush by Martin MH6	Hall bridge 1	5.029	14 channel	
4	Rush by Martin MH6	Hall bridge 1	5.043	14 channel	
5	Rush by Martin MH6	Hall bridge 2	5.057	14 channel	
6	Rush by Martin MH6	Hall bridge 2	5.071	14 channel	
7	Rush by Martin MH6	Hall bridge 2	5.085	14 channel	
8	Rush by Martin MH6	Hall bridge 2	5.099	14 channel	
9	Rush by Martin MH6	Hall bridge 2	5.113	14 channel	
10	Rush by Martin MH6	Hall bridge 2	5.127	14 channel	
11	Rush by Martin MH6	Hall bridge 3	5.141	14 channel	
12	Rush by Martin MH6	Hall bridge 3	5.155	14 channel	
13	Rush by Martin MH6	Hall bridge 3	5.169	14 channel	
14	Rush by Martin MH6	Hall bridge 3	5.183	14 channel	
1	MDG Atme	Hall Bridge side	5.501	3 channel	
1	LOOK Viper 2.6	Hall Bridge side	5.500	1 channel	

Universe 7 Floor

Nr.	Fixture Name	Location	DMX Address	Mode	Notes
1	Chauvet Maverick force 2 profile	Floor	7.001	50CH	
2	Chauvet Maverick force 2 profile	Floor	7.051	50CH	
3	Chauvet Maverick force 2 profile	Floor	7.101	50CH	
4	Chauvet Maverick force 2 profile	Floor	7.151	50CH	
5	Chauvet Maverick force 2 profile	Floor	7.201	50CH	
6	Chauvet Maverick force 2 profile	Floor	7.251	50CH	